



# Clover Kitchen Display System - 14"

## Specifications

### Main System

Processor	Qualcomm Snapdragon 660 Octa Core Processor, 1.8GHz 4 Cores and 2.2GHz 4 Cores
Memory	2GB LPDDR4x
Storage	16GB eMMC
OS	Android 10.x, multi-language support

### Displays

Display	14.0" IPS FHD Display Chemically strengthened cover glass with Anti-glare, Anti-fingerprint coating
---------	--

### Form Factor and Specifications

Dimensions (L x W x H)	Bundle Overbox Dimension: 19.2 x 11 x 3.3 in. / 488 x 278 x 85 mm Kitchen Display System: 13.3 x 8.2 x 1.38 in. / 338 x 208.3 x 35.15 mm
Gross Weight (Package weight)	6.4 pounds (2.9 kg)
Device Weight (Does not include AC adapter)	Kitchen Display: 3.75 pounds (1.7 kg)
AC Adaptor and Power Specs	AC input: 100-240 V, 1.5 A, 50-60 Hz; DC output: 12 V, 3.3 A Power-over-Ethernet (PoE): PoE+, IEEE 802.3at
Audio/Microphone	Bi-directional Dynamic speakers
Employee Login Method	Employee Passcode

### Ports and Connectivities

Ports (e.g. USB, Ethernet)	2x USB Type A ports (2x @ 5V/1A output) Wired LAN -10/100 fast Ethernet port
Wi-Fi Connectivity	802.11a/b/g/n/ac, 2.4GHz and 5GHz
LAN Connectivity	Wired LAN -10/100 Fast Ethernet
WWAN Connectivity	Not Available



## Environmental Conditions

Operating Temperature	Operating range 0°C–50°C (32°F–122°F)
Operating Humidity	Non-Condensing 10% to 90% Relative Humidity
Storage Temperature	Storage -20°C–60°C (-4°F–140°F)
Operating Altitude	Tested to 10000 ft.
Water Proof	Tested to IPX4
Dust Proof	IP5X

## Device Accessibility

Volume control (incl. in-built speaker, which is loud enough to be heard in noisy environments e.g. café or bar)	Through UI
Voice assistant (clear, human-quality voice)	Yes, Google talkback
Ability to connect to a stylus pen (e.g. for motor skill deficiencies)	Yes (passive stylus pen)
Ability to connect headphones	Yes (via USB), no wireless support
High contrast theme	Yes
Font size adjustment	Yes
Brightness adjustment	Yes
Universal switch	Yes

## Accessories

Available for Purchase	3rd party accessories - Wall mount, Countertop Stand
------------------------	--